

# DRY

## MOTORCYCLE BATTERIES

### CONVENTIONAL BATTERY

**ROBUST TECHNOLOGY. RELIABLE STARTING POWER.**

Landport DRY is a conventional battery with robust technology which delivers reliable starting power and ensures a long life. This lead-acid battery is dry pre-charged and comes with or without a separate acid pack for initial filling. Suitable for almost any motorcycle or scooter with basic power needs. Best choice for customers who are looking for a cheap, reliable starter battery. Available in a range of 6V and 12V batteries from 2Ah to 30Ah.




#### FEATURES

CONVENTIONAL BATTERY

ROBUST TECHNOLOGY

RELIABLE STARTING POWER

#### OFFICIAL DISTRIBUTOR



**power on command**



## MODELS AND SPECIFICATIONS

| Model         | Article number   | Voltage (V) | Capacity Ah (10hr) | CCA A (EN) | Length (mm) | Width (mm) | Height (mm) | Total height (mm) | Layout | Terminal |
|---------------|------------------|-------------|--------------------|------------|-------------|------------|-------------|-------------------|--------|----------|
| 6N2-2A        | MA 6N2-2A        | 6           | 2                  | 10         | 70          | 46         | 97          | 97                |        |          |
| 6N2A-2C-3     | MA 6N2A-2C-3     | 6           | 2                  | 10         | 71          | 47         | 105         | 105               |        |          |
| 6N4A-4D       | MA 6N4A-4D       | 6           | 4                  | 10         | 60          | 60         | 130         | 130               |        |          |
| 6N4C-1B       | MA 6N4C-1B       | 6           | 4                  | 10         | 69          | 70         | 104         | 104               |        |          |
| 6N4-2A        | MA 6N4-2A        | 6           | 4                  | 10         | 71          | 71         | 94          | 94                |        |          |
| 6N4-2A-4      | MA 6N4-2A-4      | 6           | 4                  | 10         | 71          | 71         | 94          | 94                |        |          |
| 6N4-2A-7      | MA 6N4-2A-7      | 6           | 4                  | 10         | 71          | 71         | 94          | 94                |        |          |
| 6N4B-2A       | MA 6N4B-2A       | 6           | 4                  | 10         | 101         | 47         | 95          | 95                |        |          |
| 6N4B-2A-3     | MA 6N4B-2A-3     | 6           | 4                  | 10         | 101         | 47         | 95          | 95                |        |          |
| 6N5,5-1D      | MA 6N5,5-1D      | 6           | 5,5                | 10         | 88          | 70         | 98          | 98                |        |          |
| 6N6-1D-2      | MA 6N6-1D-2      | 6           | 6                  | 30         | 99          | 56         | 109         | 109               |        |          |
| 6N6-3B        | MA 6N6-3B        | 6           | 6                  | 30         | 99          | 58         | 109         | 109               |        |          |
| 6N6-3B-1      | MA 6N6-3B-1      | 6           | 6                  | 30         | 99          | 58         | 109         | 109               |        |          |
| 6N7-1 (B39-6) | MA 6N7-1 (B39-6) | 6           | 7                  | 30         | 125         | 48         | 125         | 125               |        |          |
| B49-6         | MA B49-6         | 6           | 10                 | 40         | 90          | 83         | 161         | 161               |        |          |
| 6N11A-1B      | MA 6N11A-1B      | 6           | 11                 | 80         | 120         | 60         | 131         | 131               |        |          |
| 6N11A-3A      | MA 6N11A-3A      | 6           | 11                 | 80         | 120         | 60         | 131         | 131               |        |          |
| 6N11A-4       | MA 6N11A-4       | 6           | 11                 | 80         | 120         | 60         | 131         | 131               |        |          |
| 6N12A-2C      | MA 6N12A-2C      | 6           | 12                 | 80         | 154         | 55         | 115         | 115               |        |          |
| 6N12A-2D      | MA 6N12A-2D      | 6           | 12                 | 80         | 154         | 55         | 115         | 115               |        |          |
| B38-6A        | MA B38-6A        | 6           | 13                 | 30         | 117         | 82         | 160         | 160               |        |          |
| YB2,5L-C2     | MA YB2,5L-C2     | 12          | 2,5                | 10         | 80          | 70         | 106         | 106               |        |          |
| YB3L-A        | MA YB3L-A        | 12          | 3                  | 30         | 100         | 57         | 110         | 110               |        |          |
| YB3L-B        | MA YB3L-B        | 12          | 3                  | 30         | 100         | 57         | 110         | 110               |        |          |
| YB4L-A        | MA YB4L-A        | 12          | 4                  | 50         | 121         | 71         | 92          | 92                |        |          |
| YB4L-B        | MA YB4L-B        | 12          | 4                  | 50         | 121         | 71         | 92          | 92                |        |          |
| YB5L-B        | MA YB5L-B        | 12          | 5                  | 60         | 120         | 60         | 130         | 130               |        |          |
| 12N5,5A-3B    | MA 12N5,5A-3B    | 12          | 5,5                | 55         | 105         | 91         | 115         | 115               |        |          |
| 12N5,5-3B     | MA 12N5,5-3B     | 12          | 5,5                | 55         | 135         | 60         | 130         | 130               |        |          |
| 12N5,5-4A     | MA 12N5,5-4A     | 12          | 5,5                | 55         | 135         | 60         | 130         | 130               |        |          |
| 12N5,5-4B     | MA 12N5,5-4B     | 12          | 5,5                | 55         | 135         | 60         | 130         | 130               |        |          |
| YB7C-A        | MA YB7C-A        | 12          | 7                  | 110        | 132         | 92         | 116         | 116               |        |          |
| 12N7-3B-2     | MA 12N7-3B-2     | 12          | 7                  | 70         | 137         | 76         | 133         | 133               |        |          |
| 12N7-4B       | MA 12N7-4B       | 12          | 7                  | 70         | 137         | 76         | 133         | 133               |        |          |

| Model      | Article number | Voltage (V) | Capacity Ah (10hr) | CCA A (EN) | Length (mm) | Width (mm) | Height (mm) | Total height (mm) | Layout | Terminal |
|------------|----------------|-------------|--------------------|------------|-------------|------------|-------------|-------------------|--------|----------|
| YB7-A      | MA YB7-A       | 12          | 7                  | 110        | 137         | 76         | 133         | 133               |        |          |
| YB7L-B     | MA YB7L-B      | 12          | 7                  | 110        | 137         | 76         | 133         | 133               |        |          |
| YB9A-A     | MA YB9A-A      | 12          | 9                  | 115        | 137         | 76         | 152         | 152               |        |          |
| YB9B       | MA YB9B        | 12          | 9                  | 115        | 137         | 76         | 139         | 139               |        |          |
| YB9L-A2    | MA YB9L-A2     | 12          | 9                  | 120        | 137         | 76         | 139         | 139               |        |          |
| YB9L-B     | MA YB9L-B      | 12          | 9                  | 115        | 137         | 76         | 139         | 139               |        |          |
| YB10L-A2   | MA YB10L-A2    | 12          | 11                 | 140        | 135         | 90         | 145         | 145               |        |          |
| YB10L-B    | MA YB10L-B     | 12          | 11                 | 140        | 135         | 90         | 145         | 145               |        |          |
| YB10L-B2   | MA YB10L-B2    | 12          | 11                 | 140        | 135         | 90         | 145         | 145               |        |          |
| YB12A-A    | MA YB12A-A     | 12          | 12                 | 160        | 134         | 80         | 160         | 160               |        |          |
| YB12A-B    | MA YB12A-B     | 12          | 12                 | 160        | 134         | 80         | 160         | 160               |        |          |
| YB12AL-A   | MA YB12AL-A    | 12          | 12                 | 160        | 134         | 80         | 160         | 160               |        |          |
| YB12AL-A2  | MA YB12AL-A2   | 12          | 12                 | 160        | 134         | 80         | 160         | 160               |        |          |
| YB12C-A    | MA YB12C-A     | 12          | 12                 | 160        | 135         | 80         | 174         | 174               |        |          |
| YB12B-B2   | MA YB12B-B2    | 12          | 12                 | 160        | 160         | 90         | 131         | 131               |        |          |
| YB14-A2    | MA YB14-A2     | 12          | 14                 | 180        | 135         | 91         | 166         | 166               |        |          |
| YB14A-A2   | MA YB14A-A2    | 12          | 14                 | 180        | 135         | 90         | 177         | 177               |        |          |
| YB14-B2    | MA YB14-B2     | 12          | 14                 | 180        | 135         | 91         | 166         | 166               |        |          |
| YB14L-A2   | MA YB14L-A2    | 12          | 14                 | 180        | 135         | 91         | 166         | 166               |        |          |
| YB14L-B2   | MA YB14L-B2    | 12          | 14                 | 180        | 135         | 91         | 166         | 166               |        |          |
| HYB16A-A   | MA HYB16A-A    | 12          | 16                 | 200        | 148         | 88         | 180         | 180               |        |          |
| YB16B-A    | MA YB16B-A     | 12          | 16                 | 200        | 157         | 89         | 162         | 162               |        |          |
| YB16B-A1   | MA YB16B-A1    | 12          | 16                 | 200        | 157         | 89         | 162         | 162               |        |          |
| YB16AL-A2  | MA YB16AL-A2   | 12          | 16                 | 200        | 206         | 70         | 164         | 164               |        |          |
| YB18A      | MA YB18A       | 12          | 18                 | 200        | 181         | 90         | 160         | 160               |        |          |
| YB18L-A    | MA YB18L-A     | 12          | 18                 | 200        | 181         | 90         | 160         | 160               |        |          |
| YB16B      | MA YB16B       | 12          | 19                 | 240        | 175         | 99         | 155         | 155               |        |          |
| YB16CL-B   | MA YB16CL-B    | 12          | 19                 | 240        | 175         | 100        | 175         | 175               |        |          |
| YB16L-B    | MA YB16L-B     | 12          | 19                 | 240        | 175         | 99         | 155         | 155               |        |          |
| 12Y16A-3B  | MA 12Y16A-3B   | 12          | 19                 | 240        | 185         | 81         | 169         | 169               |        |          |
| Y50N18LA2  | MA Y50N18LA2   | 12          | 20                 | 260        | 205         | 90         | 162         | 162               |        |          |
| Y60-N24L-A | MA Y60-N24L-A  | 12          | 24                 | 260        | 187         | 128        | 167         | 167               |        |          |
| YHD4-12    | MA YHD4-12     | 12          | 29                 | 260        | 202         | 131        | 163         | 163               |        |          |
| YB30CL-B   | MA YB30CL-B    | 12          | 30                 | 300        | 167         | 131        | 192         | 192               |        |          |
| YB30L-B    | MA YB30L-B     | 12          | 30                 | 300        | 167         | 131        | 176         | 176               |        |          |
| Y60-N30-A  | MA Y60-N30-A   | 12          | 30                 | 300        | 187         | 128        | 167         | 167               |        |          |
| Y60-N30L-A | MA Y60-N30L-A  | 12          | 30                 | 300        | 187         | 128        | 167         | 167               |        |          |

## MODELS AND SPECIFICATIONS

| Model       | Article number | Voltage (V) | Capacity Ah (10hr) | CCA A (EN) | Length (mm) | Width (mm) | Height (mm) | Total height (mm) | Layout | Terminal |
|-------------|----------------|-------------|--------------------|------------|-------------|------------|-------------|-------------------|--------|----------|
| YB3L-A      | MB YB3L-A      | 12          | 3                  | 30         | 100         | 57         | 110         | 110               |        |          |
| YB3L-B      | MB YB3L-B      | 12          | 3                  | 30         | 100         | 57         | 110         | 110               |        |          |
| YB4L-B      | MB YB4L-B      | 12          | 4                  | 50         | 121         | 71         | 92          | 92                |        |          |
| YB5L-B      | MB YB5L-B      | 12          | 5                  | 60         | 120         | 60         | 130         | 130               |        |          |
| YB7C-A      | MB YB7C-A      | 12          | 8                  | 110        | 132         | 92         | 116         | 116               |        |          |
| YB7-A       | MB YB7-A       | 12          | 8                  | 110        | 137         | 76         | 133         | 133               |        |          |
| YB7L-B      | MB YB7L-B      | 12          | 8                  | 110        | 137         | 76         | 133         | 133               |        |          |
| YB9B        | MB YB9B        | 12          | 9                  | 115        | 137         | 76         | 139         | 139               |        |          |
| YB9L-B      | MB YB9L-B      | 12          | 9                  | 115        | 137         | 76         | 139         | 139               |        |          |
| YB10L-A2    | MB YB10L-A2    | 12          | 11                 | 140        | 135         | 90         | 145         | 145               |        |          |
| YB10L-B     | MB YB10L-B     | 12          | 11                 | 140        | 135         | 90         | 145         | 145               |        |          |
| YB10L-B2    | MB YB10L-B2    | 12          | 11                 | 140        | 135         | 90         | 145         | 145               |        |          |
| YB12A-A     | MB YB12A-A     | 12          | 12                 | 160        | 134         | 80         | 160         | 160               |        |          |
| YB12A-B     | MB YB12A-B     | 12          | 12                 | 160        | 134         | 80         | 160         | 160               |        |          |
| YB12AL-A    | MB YB12AL-A    | 12          | 12                 | 160        | 134         | 80         | 160         | 160               |        |          |
| YB12AL-A2   | MB YB12AL-A2   | 12          | 12                 | 160        | 134         | 80         | 160         | 160               |        |          |
| YB14-A2     | MB YB14-A2     | 12          | 14                 | 180        | 135         | 91         | 166         | 166               |        |          |
| YB14A-A2    | MB YB14A-A2    | 12          | 14                 | 180        | 135         | 90         | 177         | 177               |        |          |
| YB14-B2     | MB YB14-B2     | 12          | 14                 | 180        | 135         | 91         | 166         | 166               |        |          |
| YB14L-A2    | MB YB14L-A2    | 12          | 14                 | 180        | 135         | 91         | 166         | 166               |        |          |
| YB14L-B2    | MB YB14L-B2    | 12          | 14                 | 180        | 135         | 91         | 166         | 166               |        |          |
| HYB16A-A    | MB HYB16A-A    | 12          | 16                 | 200        | 148         | 88         | 180         | 180               |        |          |
| YB16B-A     | MB YB16B-A     | 12          | 16                 | 200        | 157         | 89         | 162         | 162               |        |          |
| YB16B-A1    | MB YB16B-A1    | 12          | 16                 | 200        | 157         | 89         | 162         | 162               |        |          |
| YB16AL-A2   | MB YB16AL-A2   | 12          | 16                 | 200        | 206         | 70         | 164         | 164               |        |          |
| YB18L-A     | MB YB18L-A     | 12          | 18                 | 200        | 181         | 90         | 160         | 160               |        |          |
| YB16CL-B    | MB YB16CL-B    | 12          | 19                 | 240        | 175         | 100        | 175         | 175               |        |          |
| Y50N18LA2   | MB Y50N18LA2   | 12          | 20                 | 260        | 205         | 90         | 162         | 162               |        |          |
| Y60-N24A-LB | MB Y60-N24A-LB | 12          | 24                 | 260        | 187         | 128        | 167         | 167               |        |          |
| Y60-N24L-A  | MB Y60-N24L-A  | 12          | 24                 | 260        | 187         | 128        | 167         | 167               |        |          |
| YB30CL-B    | MB YB30CL-B    | 12          | 30                 | 300        | 167         | 131        | 192         | 192               |        |          |
| YB30L-B     | MB YB30L-B     | 12          | 30                 | 300        | 167         | 131        | 176         | 176               |        |          |
| Y60-N30-A   | MB Y60-N30-A   | 12          | 30                 | 300        | 187         | 128        | 167         | 167               |        |          |
| Y60-N30L-A  | MB Y60-N30L-A  | 12          | 30                 | 300        | 187         | 128        | 167         | 167               |        |          |
| Y60-N35L-A  | MB Y60-N35L-A  | 12          | 30                 | 300        | 233         | 131        | 167         | 167               |        |          |